

πλ2 Alternative Firmware PL02.56 Release Notes

- This is a tribute firmware to the 80's SP0256-AL2 speech synthesizer chip.

It removes some PL2 functionality like the digital "variable state filter" and uses a "vocal tract" filter instead.

With the PL2 editor software, you can easily go back and forth between PL02.56 and the original (e.g. V2.0) firmware.

Like on it's role model, the vocal tract filter runs at a samplerate of 10kHz. More information about the SP0256-AL2 can be found here:
http://en.wikipedia.org/wiki/General_Instrument_SP0256

- The "Digital Filter Cutoff" controller (#18/#74):

Default position is 0, higher values add an offset to the vocal tract frequencies. With some allophones this introduces noise starting at a certain point.

- The "Digital Filter Resonance" controller (#15/#71):

Default position is 63. The speed of the allophones bases on MIDI clock, normal speed equals 120bpm. With this controller you can adjust the tempo relatively to MIDI clock.

- "Mode" (#3) and Waveform (#24/#75) controllers are unused

Only Waveform #1 (Basic Pulse Wave) is available.

- "Filter Type - Digital" (#28/#79) and "PWM2" (#23/#95) are unused

"PWM 1&2" (#10) controls PWM1 only.

- There's no factory (ROM) and user presets available

Instead, there's 16 playmodes accessible via MIDI Program Change, listed at the end of this document.

Please note: User presets remain untouched while using PL02.56 firmware and are still alive, when going back to original (e.g. V2.0) firmware.

- "Modulation Wheel Mode" (#31/#82) is not available

The modulation wheel is used to select the note or allophone, as shown on the last pages of this document.

The default position of the mod wheel can be set using the PL2 editor software. This value is recalled after every program change.

The editor software is available at:
<http://www.ploytec.com/pl2>

- Each two modes use MIDI Notes, two use the Modulation Wheel for Allophone selection

Playmodes are available in alphabetical (#1-#4) and original (#5-#8) order. There's also variations without the "voiceless" and "nasal" allophones (#9-#16), see page 10f.

- On the following eight pages you'll find a great (historical) article about the SP0256-AL2 speech synthesis, including five informative tables.

This information is RadioShack Corporation (formlery known as Tandy Corporation) copyrighted material.

It is taken from the "Archer® SP0256 Narrator Speech Processor Technical Data Sheet" (Catalog No. 276-1784).

It is reproduced by kind and written permission of RadioShack:

ALLOPHONE SPEECH SYNTHESIS

Introduction

The allophone speech synthesis technique provides the user with the ability to synthesize an unlimited vocabulary at a very low bit rate. Fifty-nine discrete speech sounds (called allophones) are five pauses are stored at different addresses in the SP0256 internal ROM. Each speech sound was excised from a word and analyzed using linear predictive coding (LPC). Any English word or phrase can be created by addressing the appropriate combination of allophones and pauses. Since there is a total of 64 address locations each requires a 6 bit address. Assuming that speech contains 10 to 12 sounds per second, allophone synthesis requires addressing less than 100 bits per second.

Linguistics

A few basic linguistic concepts will help you start your own library of "allophone words". (See Table 1 for the General Instrument Allophone Dictionary). First, there is no one-to-one correspondence between written letters and speech sounds; secondly, speech sounds are acoustically different depending upon their position within a word; and lastly, the human ear may perceive the same acoustic signal differently in the context of different sounds.

The first point compares to the problem that a child encounters when learning to read. Each sound in a language may be represented by more than one letter and, conversely each letter may represent more than one sound. (See the examples in Table 2.) Because of these spelling irregularities, it is necessary to think in terms of sounds, not letters, when using allophones.

The second, and equally important, point to understand, is that the acoustic signal of a speech sound may differ depending upon its position within a word. For example, the initial **K** sound in **coop** will be acoustically different from the **K's** in **keep** and **speak**. The **K's** in **coop** and **keep** differ due to the influence of the vowels

which follow them, and the final **K** in **speak** is usually not as loud as initial **K's**.

Finally, a listener may identify the same acoustic signal differently depending on the context in which it is perceived. Don't be surprised, therefore, if an allophone word sounds slightly different when used in various phrases.

Phonemes Of English

The sounds of a language are called phonemes, and each language has a set which is slightly different from that of other languages. Table 3 contains a chart of all the consonant phonemes of English, Table 4 all the vowel phonemes.

Consonants are produced by creating an occlusion or constriction in the vocal tract which produces an aperiodic sound source. If the vocal cords are vibrating at the same time, as in the case of the voiced fricatives **VV**, **DH**, **ZZ**, and **ZH**, (See Table 5) there are two sound sources: one which is aperiodic and one which is periodic.

Vowels are usually produced with a relatively open vocal tract and a periodic sound source provided by the vibrating vocal cords. They are classified according to whether the front or back of the tongue is high or low (See Table 4), whether they are long or short, and whether the lips are rounded or unrounded. In English all rounded vowels are produced in or near the back of the mouth (**UW**, **UH**, **OW**, **AO**, **OR**, **AW**). Speech sounds which have features in common behave in similar ways. For example, the voiceless stop consonants **PP**, **TT**, and **KK** (See Table 3) should be preceded by 50-80 msec of silence, and the voiced stop consonants **BB**, **DD**, and **GG** by 10-30 msec of silence.

Allophones

Phoneme is the name given to a group of similar sounds in a language. Recall that a phoneme is acoustically different depending upon its position within a word. Each of these positional variants is an allophone of the same phoneme. An allophone, therefore, is the manifestation of a phoneme in true speech signal. It is for this reason that

our inventory of English speech sounds is called an allophone set.

How To Use The Allophone Set

(See Table 1 for instructions on how to create all the sample words mentioned in this section.) The allophone set (Refer to Table 5) contains two or three versions of some phonemes. It may be necessary to use one allophone of a particular phoneme for word-or-syllable-final position, A detailed set of guidelines for using the allophones is given in Table 5. Note that these are suggestions, not rules.

For example, DD2 sounds good in initial position and DD1 sounds good in final position, as in “daughter” and “collide”. One of the differences between the initial and final versions of a consonant is that an initial version may be longer than the final version. Therefore, to create an initial SS, you can use two SSs instead of the usual single SS at the end of a word or syllable, as in “sister”. Note that this can be done with TH, and FF, and the inherently short vowels (to be discussed below), but with no other consonants. You will want to experiment with some consonants such as str, cl) to discover which version works best in the cluster. For example, KK1 sounds good before LL as in “clown”, and KK2 sounds good before WW as in “square”. One allophone of a particular phoneme may sound better before or after back vowels and another before or after front vowels. KK3 sounds good before UH and KK1 sounds good before IY, as in “cookie”. Some sounds (PP, BB, TT, DD, KK, GG, CH, and JH) require a brief duration of silence before them. For most of these, the silence has already been added but you may decide you want to add more. Therefore there are several pauses included in the allophone set varying from 10-200 msec. To create the final sounds in the words “letter” and “little” use the allophones ER and EL.

Remember that you must always think about how a word sounds, not how it is spelled. For example, the NG sound is represented by the letter N in “uncle”, And remember that some sounds may not even be represented in words by any letters, as the YY in “computer”.

As mentioned earlier there are some vowels which can be doubled to make longer versions for stressed syllables. These are the inherently short vowels IH, EH, AE, AX, AA, and UH. For example, in the word “extent” use one EH in the first syllable, which is unstressed and two EHs in the second syllable which is stressed. Of the inherently long vowels there is one, UW , which has a long and short version.

The short one, UW1, sounds good after YY in computer. The long version, UW2, sounds good in mono-syllabic words like “two”. Included in the vowel set is a group called R-colored vowels. These are vowel + R combinations. For example, the AR in “alarm” and the OR in “score”. Of the R-colored vowels there is one, ER, which has a long and short version. The short version is good for polysyllabic words with final ER sounds like “letter”, and the long version is good for monosyllabic words like “fir”. One final suggestion is that you may want to add a pause of 30-50 msec between words, when creating sentences, and a pause of 100-200 msec between clauses.

Note: Every utterance must be followed by a pause in order to make the chip stop talking the last allophone.

Table 1:

NUMBERS:

zero	ZZ YR OW
one, won	WW AX AX NN1
two, to, too	TT2 UW2
three	TH RR1 IY
four, for, fore	FF FF OR
five	FF FF AY VV
six	SS SS IH IH PA3 KK2 SS
seven	SS SS EH EH VV IH NN1
eight, ate	EY PA3 TT2
nine	NN1 AA AY NN1
ten	TT2 EH EH NN1
eleven	IH LL EH EH VV IY NN1
twelve	TT2 WH EH EH LL VV
thirteen	TH ER1 PA2 PA3 TT2 IY NN1
fourteen	FF OR PA2 PA3 TT2 IY NN1
fifteen	FF IH FF PA2 PA3 TT2 IY NN1

sixteen SS SS IH PA3 KK2 SS
PA2 PA3 TT2 IY NN1

seventeen SS SS EH VV TH NN1
PA2 PA3 TT2 IY NN1

eighteen EY PA2 PA3 TT2 IH NN1

nineteen NN1 AY NN1 PA2 PA3
TT2 IY NN1

twenty TT2 WH EH EH NN1 PA2
PA3 TT2 IY

thirty TH ER2 PA2 PA3 TT2 IY

forty FF OR PA3 TT2 IY

fifty FF FF IH FF FF PA2 PA3
TT2 IY

sixty SS SS IH PA3 KK2 SS
PA2 PA3 TT2 IY

seventy SS SS EH VV IH NN1
PA2 PA3 TT2 IY

eighty EY PA3 TT2 IY

ninety NN1 AY NN1 PA3 TT2 IY

hundred HH2 AX AX NN1 PA2
DD2 RR2 IH IH PA1 DD1

thousand TH AA AW ZZ TH PA1
PA1 NN1 DD1

million MM IH IH LL YY1 AX NN1

DAY OF THE WEEK:

Sunday SS SS AX AX NN1 PA2
DD2 EY

Monday MM AX AX NN1 PA2 DD2
EY

Tuesday TT2 UW ZZ PA2 DD2 EY

Wednesday WW EH EH NN1 ZZ PA2
DD2 EY

Thursday TH ER2 ZZ PA2 DD2 EY

Friday FF RR2 AY PA2 DD2 EY

Saturday SS SS AE PA3 TT2 PA2
DD2 EY

MONTHS:

January JH AE AE NN1 YY2 XR IY

February FF EH EH PA1 BR RR2
UW2 XR IY

March MM AR PA3 CH

April EY PA3 PP RR2 IH IH LL

May MM EY

June JH UW2 NN1

July JH UW1 LL AY

August AO AO PA2 GG2 AX SS
PA3 TT1

September SS SS EH PA3 PP PA3
TT2 EH EH PA1 BB2 ER1

October AA PA2 KK2 PA3 TT2
OW PA1 BB2 ER1

November NN2 OW VV EH EH MM
PA1 BB2 ER1

December DD2 IY SS SS EH EH MM
PA1 BB2 ER1

LETTERS:

A EY

B BB2 IY

C SS SS IY

D DD2 IY

E IY

F EH EH FF FF

G JH IY

H EY PA2 PA3 CH

I AA AY

J JH EH EY

K KK1 EH EY

L EH EH EL

M EH EH MM

N EH EH NNI

O OW

P PP IY

Q KK1 YY1 UW2

R AR

S EH EH SS SS

T TT2 IY

U YY1 UW2

V VV IY

W DD2 AX PA2 BB2 EL YY1 UW2

X EH EH PA3 KK2 SS SS

Y WW AY

Z ZZ IY

DICTIONARY:

alarm AX LL AR MM

bathe BB2 EY DH2

bather BB2 EY DH2 ER1

bathing BB2 EY DH2 IH NG

beer BB2 YR

bread BB1 RR2 EH EH PA1
DD1

by BB2 AA AY

calendar KK1 AE AE LL EH NN1
PA2 DD2 ER1

clock KK1 LL AA AA PA3 KK2

clown KKI LL AW NN1

check CH EH EH PA3 KK2

checked CH EH EH PA3 KK2 PA2
TT2

checker CH EH EH PA3 KK1 ER1

checkers CH EH EH PA3 KK1 ER1
ZZ

checking CH EH EH PA3 KK1 IH
NG

checks	CH EH EH PA3 KK1 SS	freezer	FF FF RRI IY ZZ ER1
cognitive	KK3 AA AA GG3 NN1 IH PA3 TT2 IH VV	freezers	FF FF RR1 IY ZZ ER1 ZZ
collide	KK3 AX LL AY DD1	freezing	FF FF RR1 IY ZZ IH NG
computer	KK1 AX MM PP1 YY1 UW1 TT2 ER	frozen	FF FF RR1 OW ZZ EH NN1
cookie	KK3 UH KK1 IY	gauge	GG1 EY PA2 JH
coop	KK3 UW2 PA3 PP	guaged	GG1 EY PA2 JH PA2 DD1
correct	KK1 ER2 EH EH PA2 KK2 PA2 TT1	guager	GG1 EY PA2 JH IH ZZ
corrected	KK1 ER2 EH EH PA2 KK2 PA2 TT2 IH PA2 DD1	guaging	GG1 EY PA2 JH IH NG
correcting	KK1 ER2 EH EH PA2 KK2 PA2 TT2 IH NG	hello	HH EH LL AX OW
corrects	KK1 ER2 EH EH PA2 KK2 PA2 TT1 SS	hour	AW ER1
crown	KK1 RR2 AW NN1	infinitive	IH NN1 FF FF IH IH NM IH PA2 PA3 TT2 IH VV
date	DD2 EY PA3 TT2	intrigue	IH NN1 PA3 TT2 RR2 IY PA1 GG3
daughter	DD2 AO TT2 ER1	intrigued	IH NN1 PA3 TT2 RR2 IY PA1 GG3 PA2 DD1
day	DD2 EH EY	intrigues	IH NN1 PA3 TT2 RR2 IY PA1 GG3 ZZ
divided	DD2 IH VV AY PA2 DD2 IH PA2 DD1	intriguing	IH NN1 PA3 TT2 RR2 IY PA1 GG3 IH NG
emotional	IY MM OW SH AX NN1 AX EL	investigate	IH IH NN1 VV EH EH SS PA2 PA3 TT2 IH PA1 GG1 EY PA2 TT2
engage	EH EH PA1 NN1 GG1 EY PA2 JH	investigated	IH IH NN1 VV EH EH SS PA2 PA3 TT2 IH PA1 GG1 EY PA2 TT2 IH PA2 DD1
engagement	EH EH PA1 NN1 GG1 EY PA2 JH MM EH EH NN1 PA2 PA3 TT2	investigator	IH IH NN1 VV EH EH SS PA2 PA3 TT2 IH PA1 GG1 EY PA2 TT2 ER1
engages	EH EH PA1 NN1 GG1 EY PA2 JH IH ZZ	investigators	IH IH NN1 VV EH EH SS PA2 PA3 TT2 IH PA1 GG1 EY PA2 TT2 ER1 ZZ
engaging	EH EH PA1 NN1 GG1 EY PA2 JH IH NG	investigates	IH IH NN1 VV EH EH SS PA2 PA3 TT2 IH PA1 GG1 EY PA2 TT1 SS
enrage	EH NN1 RR1 EY PA2 JH	investigating	IH IH NN1 VV EH EH SS PA2 PA3 TT2 IH PA1 GG1 EY PA2 TT2 IH NG KK1 IY
enraged	EH NN1 RR1 EY PA2 JH PA2 DDI	key	LL EH EH PA2 JH JH SS SS LL EY PA2 PA3 TT2
enrages	EH NN1 RB1 EY PA2 JH IH ZZ	legislate	LL EH EH PA2 JH JH SS SS LL EY PA2 PA3 TT2 IH DD1
enraging	EH NN1 RR1 EY PA2 JH IH NG	legislated	LL EH EH PA2 JH JH SS SS LL EY PA2 PA3 TT2 IH DD1
escape	EH SS SS PA3 KK1 PA2 PA3 PP	legislates	LL EH EH PA2 JH JH SS SS LL EY PA2 PA3 TT1 SS
escaped	EH SS SS PA3 KK1 PA2 PA3 PP PA2 TT2	legislating	LL EH EH PA2 JH JH SS SS LL EY PA2 PA3 TT2 IH NG
escapes	EH SS SS PA3 KK1 PA2 PA3 PP SS	legislature	LL EH EH PA2 JH JH SS SS LL EY PA2 PA3 CH ER1
escaping	EH SS SS PAS KK1 PA2 PA3 PP IH NG	letter	LL EH EH PA3 TT2 ER1
equal	IY PA2 PA3 KK3 WH AX EL	litter	LL IH IH PA3 TT2 ER1
equals	IY PA2 PA3 KK3 WH AX EL ZZ		
error	EH XR OR		
extent	EH KK1 SS TT2 EH EH NN1 TT2		
fir	FF ER2		
freeze	FF FF RR1 IY ZZ		

little	LL IH IH PA3 TT2 EL	speller	SS SS PA3 PP EH EH EL ER2
memory	MM EH EH MM ER2 IY	spellers	SS SS PA3 PP EH EH EL ER2 ZZ
memories	MM EH EH MM ER2 IY ZZ	spelling	SS SS PA3 PP EH EH EL IH NG
minute	MM IH NN1 IH PA3 TT2	spells	SS SS PA3 PP EH EH EL ZZ
month	MM AX NN1 TH	start	SS SS PA3 TT2 AR PA3 TT2
nip	NN1 IH IH PA2 PA3 PP	started	SS SS PA3 TT2 AB PA3 TT2 IH PA1 DD2
nipped	NN1 IH IH PA2 PA3 PP PA3 TT2	starter	SS SS PA3 TT2 AR PA3 TT2 ER1
nipping	NN1 IH IH PA2 PA3 PP IH NG	starting	SS SS PP3 TT2 AR PA3 TT2 IH NG
nips	NN1 IH IH PA2 PA3 PP SS	starts	SS SS PP3 TT2 AR PA3 TT1 SS
no	NN2 AX OW	stop	SS SS PA3 TT1 AA AA PA3 PP
physical	FF FF IH ZZ IH PA3 KK1 AX EL	stopped	SS SS PA3 TT1 AA AA PA3 PP PA3 TT2
pin	PP IH IH NN1	stopper	SS SS PA3 TT1 AA AA PA3 PP ER1
pinned	PP IH IH NN1 PA2 DD1	stopping	SS SS PA3 TT1 AA AA PA3 FP IH NG
pinning	PP IH IH NN1 IH NG1	stops	SS SS PA3 TT1 AA AA PA3 PP SS
pins	PP IH IH NN1 ZZ	subject (noun)	SS SS AX AX PA2 BB1 PA2 JH EH PA3 KK2 PA3 TT2
pledge	PP LL EH EH PA3 JH	subject (verb)	SS SS AX PA2 BB1 PA2 JH EH EH PA3 KK2 PA3 TT2
pledged	PP LL EH EH PA3 JH PA2 DD1	sweat	SS SS WW EH EH PA3 TT2
pledges	PP LL EH EH PA3 JH IH ZZ	sweated	SS SS WW EH EH PA3 TT2 IH PA3 DD1
pledging	PP LL EH EH PA3 JH IH NG	sweater	SS SS WW EH EH PA3 TT2 ER1
plus	PP LL AX AX SS SS	sweaters	SS SS WW EH EH PA3 TT2 ER1 ZZ
ray	RR1 EH EY	sweating	SS SS WW EH EH PA3 TT2 IH NG
rays	RR1 EH EY ZZ	sweats	SS SS WW EH EH PA3 TT2 SS
ready	RR1 EH EH PA1 DD2 IY	switch	SS SS WH IH IH PA3 CH
red	RR1 EH FH PA1 DDI	switched	SS SS WH IH IH PA3 CH PA3 TT2
robot	RR1 OW PA2 BB2 AA PA3 TT2	switches	SS SS WH IH IH PA3 CH IH ZZ
robols	RR1 OW PA2 BA2 AA PA3 TT1 SS	switching	SS SS WH IH IH PA3 CH IH NG2
score	SS SS PA3 KK3 OR	system	SS SS IH IH SS SS PA3 TT2 EH MM
second	SS SS EH PA3 KK1 IH NN1 PA2 DD1	systems	SS SS IH IH SS SS PA3 TT2 EH MM ZZ
sensitive	SS SS EH EH NN1 SS SS IH PA2 PA3 TT2 IH VV		
sensitivity	SS SS EH EH NN1 SS SS IH PA2 PA3 TT2 IH VV IH PA2 PA3 TT2 IY		
sincere	SS SS IH IH NN1 SS SS YR		
sincerely	SS SS IH IH NN1 SS SS YR LL IY		
sincerity	SS SS IH IH NN1 SS SS EH EH RR1 IH PA2 PA3 TT2 IY		
sister	SS SS IH IH SS PA3 TT2 ER1		
speak	SS SS PA3 IY PA3 KK2		
spell	SS SS PA3 PP EH EH EL		
spelled	SS SS PA3 PP EH EH EL PA3 DDI		

talk	TT2 AO AO PA2 KK2
talked	TT2 AO AO PA3 KK2 PA3 TT2
talker	TT2 AO AO PA3 KK1 ER1
talkers	TT2 AO AO PA3 KK1 ER1 ZZ
talking	TT2 AO AO PA3 KK1 IH NG
talks	TT2 AO AO PA2 KK2 SS
thread	TH RR1 EH EH PA2 DD1
threaded	TH RR1 EH EH PA2 DD2 IH PA2 DD1
threader	TH RR1 EH EH PA2 DD2 ER1
threaders	TH RR1 EH EH PA2 DD2 ER1 ZZ
threading	TH RR1 EH EH PA2 DD2 IH NG
threads	TH RR1 EH EH PA2 DD2 ZZ
then	DH1 EH EH NNI
time	TT2 AA AY MM
times	TT2 AA AY MM ZZ
uncle	AX NG PA3 KK3 EL
whale	WW EY EL
whaler	WW EY LL ER1
whalers	WW EY LL ER1 ZZ
whales	WW EY EL ZZ
whaling	WW EY LL TH NG
year	YY2 YR
yes	YY2 EH EH SS SS

TABLE 2 - EXAMPLES OF SPELLING IRREGULARITIES

Same sound represented by different letters	Different sounds represented by the same letters
---	--

Vowels

mEAt	vEln
fEEt	forElgn
pEte	dElsm
pEople	dElcer
pennY	gElsha

Consonants

SHip	althouGH
tenSlon	GHastly
preClous	couGH
naTlon	hiccouGH

TABLE 5 - GUIDELINES FOR USING THE ALLOPHONES

Silence

PA1 (10ms)	- before BB, DD, GG, and JH
PA2 (30ms)	- before BB, DD, GG, and JH
PA3 (50ms)	- before PP, TT, KK, and CH, and between words
PA4 (100 ms)	- between clauses and
PA5 (200 ms)	sentences

Short Vowels

*/IH/	- sitting, stranded
*/EH/	- extent, gentlemen
*/AE/	- extract, acting
*/UH/	- cookie, full
*/AO/	- talking, song
*/AX/	- lapel, instruct
*/AA/	- pottery, cotton

Long Vowels

/IY/	- treat, people, penny
/EY/	- great, statement, tray
/AY/	- kite, sky, mighty
/OY/	- noise, toy, voice
/UW1/	- after clusters with YY: computer
/UW2/	- in monosyllabic words: two, food
/OW/	- zone, close, snow
/AW/	- sound, mouse, down
/EL/	- little, angle, gentlemen

R-Colored Vowels

/ER1/	- letter, furniture, interrupt
/ER2/	- monosyllables: bird, fern, burn
/OR/	- fortune, adorn, store
/AR/	- farm, alarm, garment
/YR/	- hear, earring, irresponsible
/XR/	- hair, declare, stare

Resonants

/WW/	- we, warrant, linguist
/RR1/	- initial position: read, write, x-ray
/RR2/	- initial clusters: brown, crane, grease
/LL/	- like, hello, steel
/YY1/	- clusters: cute, beauty, computer
/YY2/	- initial position: yes, yarn, yo-yo

Voiced Fricatives

- /VV/ - vest, prove, even
- /DH1/ - word-initial position: this, then, they
- /DH2/ - word-final and between vowels: bathe, bathing
- /ZZ/ - zoo, phase
- /ZH/ - beige, pleasure

Voiceless Fricatives

- */FF/ -) These may be doubled for initial position and
- */TH/ -) used singly in final -) position
- */SS/ -)
- /SH/ - shirt, leash, nation
- /HH1/ - before front vowels: YR, IY, IH, EY, EH, XR, AE
- /HH2/ - before back vowels: UW, UH, OW, OY, AO, OR, AR
- /WH/ - white, whim, twenty

Voiced Stops

- /BB1/ - final position: rib; between vowels: fibber, in clusters: bleed, brown
- /BB2/ - initial position before a vowel: beast
- /DD1/ - final position: played, end
- /DD2/ - initial position: down; clusters: drain
- /GG1/ - before high front vowels: YR, IY, IH, EY, EH, XR
- /GG2/ - before high back vowels: UW, UH, OW, OY, AX; and clusters: green, glue
- /GG3/ - before low vowels: AE, AW, AY, AR, AA, AO, OR, ER; and medial clusters: anger; and final position: peg

* These allophones can be doubled.

* **Short Vowels**
Rounded Vowels

Voiceless Stops

- /PP/ - pleasure, ample, trip
- /TT1/ - final clusters before SS: tests, its
- /TT2/ - all other positions: test, street
- /KK1/ - before front vowels: YR, IY, IH, EY, EH, XR, AE, ER, AX; initial clusters: cute, clown, scream
- /KK2/ - final position: speak; final clusters: task
- /KK3/ - before back vowels: UW, UH, OW, OY, OR, AR, AO; initial clusters: crane, quick, clown, scream

Affricates

- /CH/ - church, feature
- /JH/ - judge, injure

Nasal

- /MM/ - milk, alarm, ample
- /NN1/ - before front and central vowels: YR, IY, IH, EY, EH, XR, AE, ER, AX, AW, AY, UW; final clusters: earn
- /NN2/ - before back vowels: UH, OW, OY, OR, AR, AA
- /NG/ - string, anger

TABLE 4 - VOWEL PHONEMES OF ENGLISH

	FRONT	CENTRAL	BACK
High	YR		
	IY		UW#
	IH*		UH*#
Mid	EY	ER	OW#
	EH*	AX*	OY#
	XR		
Low	AE*	AW#	AO*#
		AY	OR#
		AR	
		AA*	

TABLE 3 - CONSONANT PHONEMES OF ENGLISH**

		LABIAL	LABIO-DENTAL	INTER-DENTAL	ALVEOLAR	PALATAL	VELAR	GLOTTAL
Stops:	Voiceless	PP			TT		KK	
	Voiced	BB			DD		GG	
Fricatives:	Voiceless	WH	FF	TH	SS	SH		HH
	Voiced		VV	DH	ZZ	ZH*		
Affricates:	Voiceless					CH		
	Voiced					JH		
Nasals	Voiced	MM			NN		NG*	
Resonants	Voiced	WW			RR,LL	YY		

*These do not occur in word-initial position in English.

Labial: Upper and Lower Lips
Touch or Approximate

Labio-Dental: Upper Teeth and Lower
Lip Touch

Inter-Dental: Tongue Between Teeth

Alveolar: Tip of Tongue Touches or
Approximates Alveolar
Ridge (just behind upper
teeth)

Palatal: Body of Tongue Approxi-
mates Palate (roof of mouth)

Velar: Body of Tongue Touches
Velum (posterior portion of
roof of mouth)

Glottal: Glottis (opening between
vocal cords)

(These eight pages about "ALLOPHONE SPEECH SYNTHESIS" are RadioShack Corporation copyrighted material. It is reprinted by written permission of RadioShack.)

Program #1 (MIDI #0):
 Full length playback of allophones,
 up to 64 allophones buffered

Program #2 (MIDI #1):
 No buffering, allophones
 retriggered and played on key

Pitch area (Modulation Wheel):
 #0/#1: E0, #2/#3: F0 ... #126/#127: G5

Program #3 (MIDI #2):
 No buffering, full length playback,
 allophones retriggered after
 modwheel control change

Program #4 (MIDI #3):
 No buffering, allophones
 retriggered and played on key

Free key playing, C-1 ... G9

MIDI Note	MIDI #	Allophone
C-1	0	/AR/
C#-1	1	/AW/
D-1	2	/AX/
D#-1	3	/AY/
E-1	4	/BB1/
F-1	5	/BB2/
F#-1	6	/CH/
G-1	7	/DD1/
G#-1	8	/DD2/
A-1	9	/DH1/
A#-1	10	/DH2/
B-1	11	/EH/
C0	12	/EL/
C#0	13	/ER1/
D0	14	/ER2/
D#0	15	/EY/
E0	16	/FF/
F0	17	/GG1/
F#0	18	/GG2/
G0	19	/GG3/
G#0	20	/HH1/
A0	21	/HH2/
A#0	22	/IH/
B0	23	/IY/
C1	24	/JH/
C#1	25	/KK1/
D1	26	/KK2/
D#1	27	/KK3/
E1	28	/LL/
F1	29	/MM/
F#1	30	/NG/
G1	31	/NN1/
G#1	32	PA1
A1	33	PA2
A#1	34	PA3

Modulation Wheel (MIDI #1)	
0	PA1
1	PA1
2	PA2
3	PA2
4	PA3
5	PA3
6	PA4
7	PA4
8	PA5
9	PA5
10	/AA/
11	/AA/
12	/AE/
13	/AE/
14	/AO/
15	/AO/
16	/AR/
17	/AR/
18	/AW/
19	/AW/
20	/AX/
21	/AX/
22	/AY/
23	/AY/
24	/BB1/
25	/BB1/
26	/BB2/
27	/BB2/
28	/CH/
29	/CH/
30	/DD1/
31	/DD1/
32	/DD2/
33	/DD2/
34	/DH1/

B1	35	PA4	35	/DH1/
C2	36	PA5	36	/DH2/
C#2	37	/AA/	37	/DH2/
D2	38	/AE/	38	/EH/
D#2	39	/AO/	39	/EH/
E2	40	/AR/	40	/EL/
F2	41	/AW/	41	/EL/
F#2	42	/AX/	42	/ER1/
G2	43	/AY/	43	/ER1/
G#2	44	/BB1/	44	/ER2/
A2	45	/BB2/	45	/ER2/
A#2	46	/CH/	46	/EY/
B2	47	/DD1/	47	/EY/
C3	48	/DD2/	48	/FF/
C#3	49	/DH1/	49	/FF/
D3	50	/DH2/	50	/GG1/
D#3	51	/EH/	51	/GG1/
E3	52	/EL/	52	/GG2/
F3	53	/ER1/	53	/GG2/
F#3	54	/ER2/	54	/GG3/
G3	55	/EY/	55	/GG3/
G#3	56	/FF/	56	/HH1/
A3	57	/GG1/	57	/HH1/
A#3	58	/GG2/	58	/HH2/
B3	59	/GG3/	59	/HH2/
C4	60	/HH1/	60	/IH/
C#4	61	/HH2/	61	/IH/
D4	62	/IH/	62	/IY/
D#4	63	/IY/	63	/IY/
E4	64	/JH/	64	/JH/
F4	65	/KK1/	65	/JH/
F#4	66	/KK2/	66	/KK1/
G4	67	/KK3/	67	/KK1/
G#4	68	/LL/	68	/KK2/
A4	69	/MM/	69	/KK2/
A#4	70	/NG/	70	/KK3/
B4	71	/NN1/	71	/KK3/
C5	72	/NN2/	72	/LL/
C#5	73	/OR/	73	/LL/
D5	74	/OW/	74	/MM/
D#5	75	/OY/	75	/MM/
E5	76	/PP/	76	/NG/
F5	77	/RR1/	77	/NG/
F#5	78	/RR2/	78	/NN1/
G5	79	/SH/	79	/NN1/
G#5	80	/SS/	80	/NN2/
A5	81	/TH/	81	/NN2/
A#5	82	/TT1/	82	/OR/
B5	83	/TT2/	83	/OR/

C6	84	/UH/
C#6	85	/UW1/
D6	86	/UW2/
D#6	87	/VV/
E6	88	/WH/
F6	89	/WW/
F#6	90	/XR/
G6	91	/YR/
G#6	92	/YY1/
A6	93	/YY2/
A#6	94	/ZH/
B6	95	/ZZ/
C7	96	/NN2/
C#7	97	/OR/
D7	98	/OW/
D#7	99	/OY/
E7	100	/PP/
F7	101	/RR1/
F#7	102	/RR2/
G7	103	/SH/
G#7	104	/SS/
A7	105	/TH/
A#7	106	/TT1/
B7	107	/TT2/
C8	108	/UH/
C#8	109	/UW1/
D8	110	/UW2/
D#8	111	/VV/
E8	112	/WH/
F8	113	/WW/
F#8	114	/XR/
G8	115	/YR/
G#8	116	/YY1/
A8	117	/YY2/
A#8	118	/ZH/
B8	119	/ZZ/
C9	120	PA1
C#9	121	PA2
D9	122	PA3
D#9	123	PA4
E9	124	PA5
F9	125	/AA/
F#9	126	/AE/
G9	127	/AO/

84	/OW/
85	/OW/
86	/OY/
87	/OY/
88	/PP/
89	/PP/
90	/RR1/
91	/RR1/
92	/RR2/
93	/RR2/
94	/SH/
95	/SH/
96	/SS/
97	/SS/
98	/TH/
99	/TH/
100	/TT1/
101	/TT1/
102	/TT2/
103	/TT2/
104	/UH/
105	/UH/
106	/UW1/
107	/UW1/
108	/UW2/
109	/UW2/
110	/VV/
111	/VV/
112	/WH/
113	/WH/
114	/WW/
115	/WW/
116	/XR/
117	/XR/
118	/YR/
119	/YR/
120	/YY1/
121	/YY1/
122	/YY2/
123	/YY2/
124	/ZH/
125	/ZH/
126	/ZZ/
127	/ZZ/

Program #5 (MIDI #4):
 Full length playback of allophones,
 up to 64 allophones buffered

Program #6 (MIDI #5):
 No buffering, allophones
 retriggered and played on key

Pitch area (Modulation Wheel):
 #0/#1: E0, #2/#3: F0 ... #126/#127: G5

Program #7 (MIDI #6):
 No buffering, full length playback,
 allophones retriggered after
 modwheel control change

Program #8 (MIDI #7):
 No buffering, allophones
 retriggered and played on key

Free key playing, C-1 ... G9

MIDI Note	MIDI #	Allophone
C-1	0	PA1
C#-1	1	PA2
D-1	2	PA3
D#-1	3	PA4
E-1	4	PA5
F-1	5	/OY/
F#-1	6	/AY/
G-1	7	/EH/
G#-1	8	/KK3/
A-1	9	/PP/
A#-1	10	/JH/
B-1	11	/NN1/
C0	12	/IH/
C#0	13	/TT2/
D0	14	/RR1/
D#0	15	/AX/
E0	16	/MM/
F0	17	/TT1/
F#0	18	/DH1/
G0	19	/IY/
G#0	20	/EY/
A0	21	/DD1/
A#0	22	/UW1/
B0	23	/AO/
C1	24	/AA/
C#1	25	/YY2/
D1	26	/AE/
D#1	27	/HH1/
E1	28	/BB1/
F1	29	/TH/
F#1	30	/UH/
G1	31	/UW2/
G#1	32	/AW/
A1	33	/DD2/
A#1	34	/GG3/

Modulation Wheel (MIDI #1)	
0	PA1
1	PA1
2	PA2
3	PA2
4	PA3
5	PA3
6	PA4
7	PA4
8	PA5
9	PA5
10	/OY/
11	/OY/
12	/AY/
13	/AY/
14	/EH/
15	/EH/
16	/KK3/
17	/KK3/
18	/PP/
19	/PP/
20	/JH/
21	/JH/
22	/NN1/
23	/NN1/
24	/IH/
25	/IH/
26	/TT2/
27	/TT2/
28	/RR1/
29	/RR1/
30	/AX/
31	/AX/
32	/MM/
33	/MM/
34	/TT1/

B1	35	/VV/
C2	36	/GG1/
C#2	37	/SH/
D2	38	/ZH/
D#2	39	/RR2/
E2	40	/FF/
F2	41	/KK2/
F#2	42	/KK1/
G2	43	/ZZ/
G#2	44	/NG/
A2	45	/LL/
A#2	46	/WW/
B2	47	/XR/
C3	48	/WH/
C#3	49	/YY1/
D3	50	/CH/
D#3	51	/ER1/
E3	52	/ER2/
F3	53	/OW/
F#3	54	/DH2/
G3	55	/SS/
G#3	56	/NN2/
A3	57	/HH2/
A#3	58	/OR/
B3	59	/AR/
C4	60	/YR/
C#4	61	/GG2/
D4	62	/EL/
D#4	63	/BB2/
E4	64	/KK3/
F4	65	/PP/
F#4	66	/JH/
G4	67	/NN1/
G#4	68	/IH/
A4	69	/TT2/
A#4	70	/RR1/
B4	71	/AX/
C5	72	/MM/
C#5	73	/TT1/
D5	74	/DH1/
D#5	75	/IY/
E5	76	/EY/
F5	77	/DD1/
F#5	78	/UW1/
G5	79	/AO/
G#5	80	/AA/
A5	81	/YY2/
A#5	82	/AE/
B5	83	/HH1/

35	/TT1/
36	/DH1/
37	/DH1/
38	/IY/
39	/IY/
40	/EY/
41	/EY/
42	/DD1/
43	/DD1/
44	/UW1/
45	/UW1/
46	/AO/
47	/AO/
48	/AA/
49	/AA/
50	/YY2/
51	/YY2/
52	/AE/
53	/AE/
54	/HH1/
55	/HH1/
56	/BB1/
57	/BB1/
58	/TH/
59	/TH/
60	/UH/
61	/UH/
62	/UW2/
63	/UW2/
64	/AW/
65	/AW/
66	/DD2/
67	/DD2/
68	/GG3/
69	/GG3/
70	/VV/
71	/VV/
72	/GG1/
73	/GG1/
74	/SH/
75	/SH/
76	/ZH/
77	/ZH/
78	/RR2/
79	/RR2/
80	/FF/
81	/FF/
82	/KK2/
83	/KK2/

C6	84	/BB1/
C#6	85	/TH/
D6	86	/UH/
D#6	87	/UW2/
E6	88	/AW/
F6	89	/DD2/
F#6	90	/GG3/
G6	91	/VV/
G#6	92	/GG1/
A6	93	/SH/
A#6	94	/ZH/
B6	95	/RR2/
C7	96	/FF/
C#7	97	/KK2/
D7	98	/KK1/
D#7	99	/ZZ/
E7	100	/NG/
F7	101	/LL/
F#7	102	/WW/
G7	103	/XR/
G#7	104	/WH/
A7	105	/YY1/
A#7	106	/CH/
B7	107	/ER1/
C8	108	/ER2/
C#8	109	/OW/
D8	110	/DH2/
D#8	111	/SS/
E8	112	/NN2/
F8	113	/HH2/
F#8	114	/OR/
G8	115	/AR/
G#8	116	/YR/
A8	117	/GG2/
A#8	118	/EL/
B8	119	/BB2/
C9	120	PA1
C#9	121	PA2
D9	122	PA3
D#9	123	PA4
E9	124	PA5
F9	125	/OY/
F#9	126	/AY/
G9	127	/EH/

84	/KK1/
85	/KK1/
86	/ZZ/
87	/ZZ/
88	/NG/
89	/NG/
90	/LL/
91	/LL/
92	/WW/
93	/WW/
94	/XR/
95	/XR/
96	/WH/
97	/WH/
98	/YY1/
99	/YY1/
100	/CH/
101	/CH/
102	/ER1/
103	/ER1/
104	/ER2/
105	/ER2/
106	/OW/
107	/OW/
108	/DH2/
109	/DH2/
110	/SS/
111	/SS/
112	/NN2/
113	/NN2/
114	/HH2/
115	/HH2/
116	/OR/
117	/OR/
118	/AR/
119	/AR/
120	/YR/
121	/YR/
122	/GG2/
123	/GG2/
124	/EL/
125	/EL/
126	/BB2/
127	/BB2/

Program #9 (MIDI #8):
 Full length playback of allophones,
 up to 64 allophones buffered

Program #10 (MIDI #9):
 No buffering, allophones
 retriggered and played on key

Pitch area (Modulation Wheel):
 #0/#1: E0, #2/#3: F0 ... #126/#127: G5

Program #11 (MIDI #10):
 No buffering, full length playback,
 allophones retriggered after
 modwheel control change

Program #12 (MIDI #11):
 No buffering, allophones
 retriggered and played on key

Free key playing, C-1 ... G9

MIDI Note	MIDI #	Allophone
C-1	0	/AR/
C#-1	1	/AW/
D-1	2	/AX/
D#-1	3	/AY/
E-1	4	/BB1/
F-1	5	/BB2/
F#-1	6	/ER1/
G-1	7	/DD1/
G#-1	8	/DD2/
A-1	9	/DH1/
A#-1	10	/DH2/
B-1	11	/EH/
C0	12	/EL/
C#0	13	/ER1/
D0	14	/ER2/
D#0	15	/EY/
E0	16	/ZZ/
F0	17	/GG1/
F#0	18	/GG2/
G0	19	/GG3/
G#0	20	/BB1/
A0	21	/OR/
A#0	22	/IH/
B0	23	/IY/
C1	24	/IH/
C#1	25	/ZZ/
D1	26	/ZZ/
D#1	27	/IH/
E1	28	/LL/
F1	29	/DH1/
F#1	30	/LL/
G1	31	/IH/
G#1	32	PA1
A1	33	PA2
A#1	34	PA3

Modulation Wheel (MIDI #1)	
0	PA1
1	PA1
2	PA2
3	PA2
4	PA3
5	PA3
6	PA4
7	PA4
8	PA5
9	PA5
10	/AA/
11	/AA/
12	/AE/
13	/AE/
14	/AO/
15	/AO/
16	/AR/
17	/AR/
18	/AW/
19	/AW/
20	/AX/
21	/AX/
22	/AY/
23	/AY/
24	/BB1/
25	/BB1/
26	/BB2/
27	/BB2/
28	/ER1/
29	/ER1/
30	/DD1/
31	/DD1/
32	/DD2/
33	/DD2/
34	/DH1/

B1	35	PA4
C2	36	PA5
C#2	37	/AA/
D2	38	/AE/
D#2	39	/AO/
E2	40	/AR/
F2	41	/AW/
F#2	42	/AX/
G2	43	/AY/
G#2	44	/BB1/
A2	45	/BB2/
A#2	46	/ER1/
B2	47	/DD1/
C3	48	/DD2/
C#3	49	/DH1/
D3	50	/DH2/
D#3	51	/EH/
E3	52	/EL/
F3	53	/ER1/
F#3	54	/ER2/
G3	55	/EY/
G#3	56	/ZZ/
A3	57	/GG1/
A#3	58	/GG2/
B3	59	/GG3/
C4	60	/BB1/
C#4	61	/OR/
D4	62	/IH/
D#4	63	/IY/
E4	64	/IH/
F4	65	/ZZ/
F#4	66	/ZZ/
G4	67	/IH/
G#4	68	/LL/
A4	69	/DH1/
A#4	70	/LL/
B4	71	/IH/
C5	72	/OR/
C#5	73	/OR/
D5	74	/OW/
D#5	75	/OY/
E5	76	/IH/
F5	77	/RR1/
F#5	78	/RR2/
G5	79	/ZH/
G#5	80	/OR/
A5	81	/UH/
A#5	82	/DH1/
B5	83	/RR1/

35	/DH1/
36	/DH2/
37	/DH2/
38	/EH/
39	/EH/
40	/EL/
41	/EL/
42	/ER1/
43	/ER1/
44	/ER2/
45	/ER2/
46	/EY/
47	/EY/
48	/ZZ/
49	/ZZ/
50	/GG1/
51	/GG1/
52	/GG2/
53	/GG2/
54	/GG3/
55	/GG3/
56	/BB1/
57	/BB1/
58	/OR/
59	/OR/
60	/IH/
61	/IH/
62	/IY/
63	/IY/
64	/IH/
65	/IH/
66	/ZZ/
67	/ZZ/
68	/ZZ/
69	/ZZ/
70	/IH/
71	/IH/
72	/LL/
73	/LL/
74	/DH1/
75	/DH1/
76	/LL/
77	/LL/
78	/IH/
79	/IH/
80	/OR/
81	/OR/
82	/OR/
83	/OR/

C6	84	/UH/
C#6	85	/UW1/
D6	86	/UW2/
D#6	87	/VV/
E6	88	/YY1/
F6	89	/WW/
F#6	90	/XR/
G6	91	/YR/
G#6	92	/YY1/
A6	93	/YY2/
A#6	94	/ZH/
B6	95	/ZZ/
C7	96	/OR/
C#7	97	/OR/
D7	98	/OW/
D#7	99	/OY/
E7	100	/IH/
F7	101	/RR1/
F#7	102	/RR2/
G7	103	/ZH/
G#7	104	/OR/
A7	105	/UH/
A#7	106	/DH1/
B7	107	/RR1/
C8	108	/UH/
C#8	109	/UW1/
D8	110	/UW2/
D#8	111	/VV/
E8	112	/YY1/
F8	113	/WW/
F#8	114	/XR/
G8	115	/YR/
G#8	116	/YY1/
A8	117	/YY2/
A#8	118	/ZH/
B8	119	/ZZ/
C9	120	PA1
C#9	121	PA2
D9	122	PA3
D#9	123	PA4
E9	124	PA5
F9	125	/AA/
F#9	126	/AE/
G9	127	/AO/

84	/OW/
85	/OW/
86	/OY/
87	/OY/
88	/IH/
89	/IH/
90	/RR1/
91	/RR1/
92	/RR2/
93	/RR2/
94	/ZH/
95	/ZH/
96	/OR/
97	/OR/
98	/UH/
99	/UH/
100	/DH1/
101	/DH1/
102	/RR1/
103	/RR1/
104	/UH/
105	/UH/
106	/UW1/
107	/UW1/
108	/UW2/
109	/UW2/
110	/VV/
111	/VV/
112	/YY1/
113	/YY1/
114	/WW/
115	/WW/
116	/XR/
117	/XR/
118	/YR/
119	/YR/
120	/YY1/
121	/YY1/
122	/YY2/
123	/YY2/
124	/ZH/
125	/ZH/
126	/ZZ/
127	/ZZ/

Program #13 (MIDI #12):
 Full length playback of allophones,
 up to 64 allophones buffered

Program #14 (MIDI #13):
 No buffering, allophones
 retriggered and played on key

Pitch area (Modulation Wheel):
 #0/#1: E0, #2/#3: F0 ... #126/#127: G5

Program #15 (MIDI #14):
 No buffering, full length playback,
 allophones retriggered after
 modwheel control change

Program #16 (MIDI #15):
 No buffering, allophones
 retriggered and played on key

Free key playing, C-1 ... G9

MIDI Note	MIDI #	Allophone
C-1	0	PA1
C#-1	1	PA2
D-1	2	PA3
D#-1	3	PA4
E-1	4	PA5
F-1	5	/OY/
F#-1	6	/AY/
G-1	7	/EH/
G#-1	8	/IH/
A-1	9	/IH/
A#-1	10	/IH/
B-1	11	/IH/
C0	12	/IH/
C#0	13	/RR1/
D0	14	/RR1/
D#0	15	/AX/
E0	16	/DH1/
F0	17	/DH1/
F#0	18	/DH1/
G0	19	/IY/
G#0	20	/EY/
A0	21	/DD1/
A#0	22	/UW1/
B0	23	/AO/
C1	24	/AA/
C#1	25	/YY2/
D1	26	/AE/
D#1	27	/BB1/
E1	28	/BB1/
F1	29	/UH/
F#1	30	/UH/
G1	31	/UW2/
G#1	32	/AW/
A1	33	/DD2/
A#1	34	/GG3/

Modulation Wheel (MIDI #1)	
0	PA1
1	PA1
2	PA2
3	PA2
4	PA3
5	PA3
6	PA4
7	PA4
8	PA5
9	PA5
10	/OY/
11	/OY/
12	/AY/
13	/AY/
14	/EH/
15	/EH/
16	/IH/
17	/IH/
18	/IH/
19	/IH/
20	/IH/
21	/IH/
22	/IH/
23	/IH/
24	/IH/
25	/IH/
26	/RR1/
27	/RR1/
28	/RR1/
29	/RR1/
30	/AX/
31	/AX/
32	/DH1/
33	/DH1/
34	/DH1/

B1	35	/VV/
C2	36	/GG1/
C#2	37	/ZH/
D2	38	/ZH/
D#2	39	/RR2/
E2	40	/ZZ/
F2	41	/ZZ/
F#2	42	/ZZ/
G2	43	/ZZ/
G#2	44	/LL/
A2	45	/LL/
A#2	46	/WW/
B2	47	/XR/
C3	48	/YY1/
C#3	49	/YY1/
D3	50	/ER1/
D#3	51	/ER1/
E3	52	/ER2/
F3	53	/OW/
F#3	54	/DH2/
G3	55	/OR/
G#3	56	/OR/
A3	57	/OR/
A#3	58	/OR/
B3	59	/AR/
C4	60	/YR/
C#4	61	/GG2/
D4	62	/EL/
D#4	63	/BB2/
E4	64	/IH/
F4	65	/IH/
F#4	66	/IH/
G4	67	/IH/
G#4	68	/IH/
A4	69	/RR1/
A#4	70	/RR1/
B4	71	/AX/
C5	72	/DH1/
C#5	73	/DH1/
D5	74	/DH1/
D#5	75	/IY/
E5	76	/EY/
F5	77	/DD1/
F#5	78	/UW1/
G5	79	/AO/
G#5	80	/AA/
A5	81	/YY2/
A#5	82	/AE/
B5	83	/BB1/

35	/DH1/
36	/DH1/
37	/DH1/
38	/IY/
39	/IY/
40	/EY/
41	/EY/
42	/DD1/
43	/DD1/
44	/UW1/
45	/UW1/
46	/AO/
47	/AO/
48	/AA/
49	/AA/
50	/YY2/
51	/YY2/
52	/AE/
53	/AE/
54	/BB1/
55	/BB1/
56	/BB1/
57	/BB1/
58	/UH/
59	/UH/
60	/UH/
61	/UH/
62	/UW2/
63	/UW2/
64	/AW/
65	/AW/
66	/DD2/
67	/DD2/
68	/GG3/
69	/GG3/
70	/VV/
71	/VV/
72	/GG1/
73	/GG1/
74	/ZH/
75	/ZH/
76	/ZH/
77	/ZH/
78	/RR2/
79	/RR2/
80	/ZZ/
81	/ZZ/
82	/ZZ/
83	/ZZ/

C6	84	/BB1/
C#6	85	/UH/
D6	86	/UH/
D#6	87	/UW2/
E6	88	/AW/
F6	89	/DD2/
F#6	90	/GG3/
G6	91	/VV/
G#6	92	/GG1/
A6	93	/ZH/
A#6	94	/ZH/
B6	95	/RR2/
C7	96	/ZZ/
C#7	97	/ZZ/
D7	98	/ZZ/
D#7	99	/ZZ/
E7	100	/LL/
F7	101	/LL/
F#7	102	/WW/
G7	103	/XR/
G#7	104	/YY1/
A7	105	/YY1/
A#7	106	/ER1/
B7	107	/ER1/
C8	108	/ER2/
C#8	109	/OW/
D8	110	/DH2/
D#8	111	/OR/
E8	112	/OR/
F8	113	/OR/
F#8	114	/OR/
G8	115	/AR/
G#8	116	/YR/
A8	117	/GG2/
A#8	118	/EL/
B8	119	/BB2/
C9	120	PA1
C#9	121	PA2
D9	122	PA3
D#9	123	PA4
E9	124	PA5
F9	125	/OY/
F#9	126	/AY/
G9	127	/EH/

84	/ZZ/
85	/ZZ/
86	/ZZ/
87	/ZZ/
88	/LL/
89	/LL/
90	/LL/
91	/LL/
92	/WW/
93	/WW/
94	/XR/
95	/XR/
96	/YY1/
97	/YY1/
98	/YY1/
99	/YY1/
100	/ER1/
101	/ER1/
102	/ER1/
103	/ER1/
104	/ER2/
105	/ER2/
106	/OW/
107	/OW/
108	/DH2/
109	/DH2/
110	/OR/
111	/OR/
112	/OR/
113	/OR/
114	/OR/
115	/OR/
116	/OR/
117	/OR/
118	/AR/
119	/AR/
120	/YR/
121	/YR/
122	/GG2/
123	/GG2/
124	/EL/
125	/EL/
126	/BB2/
127	/BB2/

Ploytec's Number Table:

Zero	/ZZ/ /EH/ /EH/ /ER1/ /OW/ /PA1/
One	/WW/ /AX/ /NN1/ /PA1/
Two	/TT2/ /UW2/ /PA1/
Three	/TH/ /RR2/ /IY/ /PA1/
Four	/FF/ /OW/ /ER1/ /PA1/
Five	/FF/ /AO/ /AY/ /FF/ /PA1/
Six	/SS/ /IH/ /IH/ /KK1/ /SS/ /PA1/
Seven	/SS/ /EH/ /VV/ /EH/ /EH/ /NN1/ /PA1/
Eight	/EY/ /DH2/ /TT2/ /PA1/
Nine	/NN1/ /AY/ /NN1/ /PA1/
Ten	/TT2/ /EH/ /EH/ /NN1/ /PA1/
Eleven	/EH/ /LL/ /EH/ /VV/ /EH/ /NN1/ /PA1/
Twelve	/TT2/ /WW/ /EH/ /LL/ /FF/ /PA1/
Thirteen	/TH/ /ER2/ /TT2/ /IY/ /NN1/ /PA1/
Fourteen	/FF/ /OW/ /ER1/ /TT2/ /IY/ /NN1/ /PA1/
Fifteen	/FF/ /IH/ /IH/ /FF/ /TT2/ /IY/ /NN1/ /PA1/
Sixteen	/SS/ /IH/ /KK1/ /SS/ /TT2/ /IY/ /NN1/ /PA1/
Seventeen	/SS/ /EH/ /VV/ /EH/ /NN1/ /TT2/ /IY/ /NN1/ /PA1/
Eighteen	/EY/ /DH2/ /TT2/ /IY/ /NN1/ /PA1/
Nineteen	/NN1/ /AY/ /NN1/ /TT2/ /IY/ /NN1/ /PA1/
Twenty	/TT2/ /WW/ /EH/ /NN1/ /TT2/ /IY/ /PA1/

Copyright 2014:

Ploytec GmbH

Fahrnauerstr. 64

79650 Schopfheim

Germany

<http://www.ploytec.com>

info@ploytec.com

The information in this document is subject to copyright. All rights are reserved. No part of this manual may be reproduced or transmitted in any form or for any purpose without the expressed written permission of the copyright holders. Product and brand names contained in this document are used for identification purposes only. All registered trademarks, product designations or brand names used in this document are the registered property of their respective owners.